



Radio Remote Control 2 Channels Single Speed Multi voltage Range 300 ft

Características Esenciales

- 200 Auto Channels replacing traditional single channel quartz plus 1 Million ID Codes.
- Easy Pairing System, no need of software or copier to add or replace lost or broken Transmitter
- Customizable 200 Functions settings to meet any special requirements
- Reinforced fiber plastic case for Transmitter and Receiver plus rubber protector for Transmitter
- 1 Años de Garantía, Partes y Servicios Disponibles en América

Especificaciones Técnicas

Codigo FCC	2AZMK-Q1212	Código de Seguridad	200 Millions
Botones	3	Potencia del Transmisor	≤10dBm
Fuente de Alimentación del Transmisor	2 AA batteries	Rango de Frecuencia	433/480 MHz
Material	PA6 30% GF	Parada de Emergencia	YES
Fuente de Alimentación del Receptor	AC 110V-480V	Rango de temperatura de Trabajo	-40 ~ 185 °F / -40 ~ 85°C
Sensibilidad del Receptor	dBm -112	Normas	FCC and OSHA standard 1910.179
Distancia de Control	300 ft / 100 mt	Garantía	1 Year

Peso & Dimensiones

A Altura Total	5.3
W Ancho	2.7
D Depth	1.2
Peso Total	2 lbs / 1 Kg

Detalles del Empaque

Paquete 1 Peso Neto	3 lbs / 1 Kg
Paquete 1 Ancho	5 in / 12.7 cm
Paquete 1 Peso Bruto	2 lbs / 1 Kg
Paquete 1 Altura	5 in / 12.7 cm
Paquete 1 Profundidad	5 in / 12.7 cm

Referential Images / Imágenes Referenciales
Specifications may change without notice / las especificaciones pueden cambiar sin previo aviso